



# **Protek Device Torque Settings**

Brass Earth and Neutral Bars: **3.0Nm**

MCBs - 1,2 and 3 Poles (upto 63A): **2.0Nm**

MCBs - 1,2,3 and 4 Pole (80A-100A): **3.5Nm**

HDMCBs - 1,2 and 3 Poles: **2.0Nm**

Isolators up to 125 A - 2,3 and 4 Pole: **2.5Nm**

RCBOs - Large Screw: **2.0Nm**

RCBOs - Small Screw: **1.8Nm**

SRCBOs: **1.2Nm**

**Nm = Newton Meters.**